



LMR BATTERY SPECIFICATIONS	PART NUMBER
	BP8299MH

COMPATIBLE RADIOS	Motorola XTS3000, XTS3500, XTS5000, Cosmo / Datron Guardian G25RPV100
REPLACES OEM BATTERY	NTN8923AR
COMPATIBLE CHARGERS	Endura TWC1-MT13B, TWC1M-MT13B, TWC2M-MT13-D, TWC6M-MT13B, TWC12M-MT13-D
VOLTAGE	7.5V
CAPACITY	2000 mAh
CHEMISTRY	NiMH
CELL TYPE	Sanyo, Panasonic, or equivalent
OPERATING TEMPERATURE	-10° C to +65° C (discharge) / 0° C to +40° C (charge)
CHARGE CYCLES	500
CHARGE TYPE	Rapid or trickle
CONDITIONER COMPATIBLE	Yes
THERMAL PROTECTION	Yes
HOUSING MATERIAL	ABS
HOUSING SEAL	Ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welder
CLIP	Included
WARRANTY	12 months
PRODUCT PHOTO	