



LMR BATTERY SPECIFICATIONS	PART NUMBER
	BP8299MHUC

COMPATIBLE RADIOS	Motorola XTS3000, XTS3500, XTS5000
REPLACES OEM BATTERY	RNN4006B (3500 mAh)
COMPATIBLE CHARGERS	Endura EC1-MT13B, EC1M-MT13B, EC2M-MT13-D, EC6M-MT13B, EC12M-MT13-D, EVC-MT13, EVC-MT13-4 / Motorola NTN1667A
VOLTAGE	7.5V
CAPACITY	3800 mAh typical (3700 mAh minimum)
CHEMISTRY	NiMH
CELL TYPE	Panasonic BK380A or equivalent
CHARGE CYCLES	500
CHARGE TYPE	Rapid or trickle
OPERATING TEMPERATURE	-10° C to +65° C (discharge) / 0° C to +45° C (charge)
CONDITIONER COMPATIBLE	Yes
PROTECTION TYPES	Over-charge / over-discharge / over-temperature
HOUSING MATERIAL	ABS
HOUSING SEAL	Ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welder
CLIP	Included
WARRANTY	12 months
PRODUCT PHOTO	